

MASTERFORCE®

PB TYPE PUMP

BASIC CONFIGURATION OF PB		MODE OF OPERATION OF THE POWERED TOOL						EFFICIENCY GROUP				
		single acting	double acting	A0- three-way, two-position	A1- three-way, two-position	B0- four-way, three-position	B1- four-way, three-position	oil flow of 0,2l/min at 700 bar		oil flow of 0,3l/min at 700 bar		
WITHOUT A VALVE		VALVE TYPE						ENGINE TYPE		ENGINE TYPE		
		0,37 kW		0,55 kW		Pressure 115 V	Pressure 115 V	Pressure 115 V	Pressure 115 V			
WITHOUT A VALVE	For external valves with necessary connection board ordered											
WITH MANUAL VALVES	A connection board suitable for the valve model. For use with one- and two-way operation tools; in connection with a manual or foot remote control responsible for the engine operation ensures full control of the pump operation.	●		●				PB E 037 115 020 - - - - 04	PB E 037 230 020 - - - - 04	PB E 055 115 030 - - - - 04	PB E 055 230 030 - - - - 04	
		●			●			PB E 037 115 020 R 1 A0 04	PB E 037 230 020 R 1 A0 04	PB E 055 115 030 R 1 A0 04	PB E 055 230 030 R 1 A0 04	
			●			●			PB E 037 115 020 R 1 A1 04	PB E 037 230 020 R 1 A1 04	PB E 055 115 030 R 1 A1 04	PB E 055 230 030 R 1 A1 04
			●				●		PB E 037 115 020 R 2 B0 04	PB E 037 230 020 R 2 B0 04	PB E 055 115 030 R 2 B0 04	PB E 055 230 030 R 2 B0 04
WITH ELECTRICAL VALVES	A connection board suitable for the valve model. For use with one- and two-way operation tools; in connection with a manual or foot remote control responsible for the engine operation ensures free use of the powered tools.			●				PB E 037 115 020 R 2 B1 04	PB E 037 230 020 R 2 B1 04	PB E 055 115 030 R 2 B1 04	PB E 055 230 030 R 2 B1 04	
		●		●				PB E 037 115 020 E 1 A0 04	PB E 037 230 020 E 1 A0 04	PB E 055 115 030 E 1 A0 04	PB E 055 230 030 E 1 A0 04	
		●			●				PB E 037 115 020 E 1 A1 04	PB E 037 230 020 E 1 A1 04	PB E 055 115 030 E 1 A1 04	PB E 055 230 030 E 1 A1 04
			●			●			PB E 037 115 020 E 2 B0 04	PB E 037 230 020 E 2 B0 04	PB E 055 115 030 E 2 B0 04	PB E 055 230 030 E 2 B0 04
		●				●		PB E 037 115 020 E 2 B1 04	PB E 037 230 020 E 2 B1 04	PB E 055 115 030 E 2 B1 04	PB E 055 230 030 E 2 B1 04	